

KNX Training Center, Taiwan

KNX Advanced Course Test 001

Task1:

Set up new project:

- Project name: <Your Name>.

Task2:

Set up Building structure.

- Building: Training Center.
- Floor: Ground floor.
- Room: Training Room.

Task3:

Complete the following function in the Training Room:

Touch Panel:

Page1:Home

- Box1: Left Button -L1 OFF.
Right Button -L1 ON.
- Box2: Single Button -L2 ON/OFF.
- Box3: Left Button Short Press-D1 OFF.
Left Button Long Press-D1 Dimming Down.
Right Button Short Press-D1 ON.
Right Button Long Press-D1 Dimming UP.
- Box4: Left Button Short Press-Blinds Step up/Stop.
Left Button Long Press-Blinds Move Down.
Right Button Short Press-Blinds Step down/Stop.
Right Button Long Press-Blinds Move UP.
- Box5: Single Button -D1 70%.
- Box6: Single Button -Blind 30%

KNX Training Center, Taiwan

KNX Advanced Course Test 001

Page2:AC Control

- Box1: Left Button -AC ON.
Right Button -AC OFF.
Middle- Indicates the AC Status.
- Box2: Left Button -Temperature Setpoint Up.
Right Button - Temperature Setpoint Dwon.
Middle- Indicates the set temperature.
- Box3: Left Button -Fan Speed Up(none cycle).
Right Button - Fan Speed Down(none cycle).
- Box4: Left Button -Valve ON.
Right Button -Valve OFF.
Middle- Indicates the Valve Status.
- Box5: Indicates the Room temperature.
- Box6: Indicates the Outdoor temperature.

Other Function:

- When Switch is turned ON, press the button L1. L2 turn OFF. Blind move Down and D1 brighter to 50%.
- When Switch is turned OFF, Button no function.

Other provisions:

- The total running time is 10 seconds of blinds.

Finish